

**TABLE 1. 16-BIT CHANNEL MODE**

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Intensity high	0-65535	16-bit control of dimming
2	Intensity low		
3	Strobe speed	0-255	0.5hz to 30hz
4	Strobe control	0-255 000-005 006-010 011-015 016-020 021-025 026-255	Open Closed Normal Strobe Random Strobe Random Sync Reserved Values
5	Control channel	000-005 006-010 011-015 016-020 021-025 026-030 031-035 036-040 041-045 046-050 051-055 056-060 061-065 066-070 071-075 076-080 081-085 086-090 091-100 101-110 111-120 121-130 131-255	Idle(Default) Full Luminaire ReCal - Also Used to Wake fixture up from shutdown Reserved Values Reserved Values Fixture Shutdown Display - Menu ON Display - Menu OFF Dimming Curve Linear Dimming Curve S-Curve Dimming Curve Square Curve (Default) Reserved Values Reserved Values Dimmer Snap On Dimmer Snap Off (Default) Color Calibration on Color Calibration off (Default) Standard Mode Studio Mode Whisper Mode Reserved Values Fan On (Default) Fan Auto Reserved Values

**TABLE 2. 8-BIT CHANNEL MODE**

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Intensity	0-255	8-bit control of dimming
2	Strobe speed	0-255	0.5hz to 30hz
3	Strobe control	0-255 000-005 006-010 011-015 016-020 021-025 026-255	Open Closed Normal Strobe Random Strobe Random Sync Reserved Values
4	Control channel	000-005 006-010 011-015 016-020 021-025 026-030 031-035 036-040 041-045 046-050 051-055 056-060 061-065 066-070 071-075 076-080 081-085 086-090 091-100 101-110 111-120 121-130 131-255	Idle(Default) Full Luminaire ReCal Reserved Values Reserved Values Fixture Shutdown Display - Menu ON Display - Menu OFF Dimming Curve Linear Dimming Curve S-Curve Dimming Curve Square Curve (Default)** Reserved Values Reserved Values Dimmer Snap On Dimmer Snap Off (Default) Color Calibration on Color Calibration off (Default) Standard Mode Studio Mode Whisper Mode Reserved Values Fan On (Default) Fan Auto Reserved Values

**TABLE 3. SINGLE CHANNEL MODE**

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Intensity	0-255	8-bit control of dimming